



➤ DMR: THE FUTURE OF TWO-WAY DIGITAL RADIO

By Mike Swiatkowski, AA9VI (aa9vi@arrl.net)

Free permission to reuse for amateur presentations – MAY 2013





MOTOROLA



simoco

JVCKENWOOD

Vertex Standard

Hytera

IRISUN

taik
communications


Digital Mobile Radio

- An ETSI published worldwide standard
- Over a HALF DOZEN manufacturers of DMR radios
- Superior voice quality over older digital modes
- Longer battery life
- Supports multiple talk groups on one channel
- Supports data applications
- Commercial ETSI/TIA specs mean rugged performance over temperature and congested urban RF environments


TWO Repeaters in One!

TDMA saves licensing and equipment costs by enabling the equivalent of two 6.25 kHz channels within a single licensed 12.5 kHz channel

Two-channel Analog or Digital FDMA System




Two-channel Digital TDMA System




*Lower infrastructure cost, 1 box in rack
TWO voice channels from one repeater*

Half the Channel Bandwidth



Traditional Analog
25 kHz
Channel Bandwidth


1 Channel
1 Repeater



DMR
12.5 kHz
Channel Bandwidth


2 Channels
1 Repeater

More Spectrum Efficient than Older Digital Modes



Guard Band
as large as 10 kHz
between channels


Total BW= 22.5 kHz



No Guard Band
between 2
channels

Total BW= 12.5 kHz

Better Signal Quality



Digital voice retains better quality than analog as signal strength decreases.

- No hiss, popping, or static
- Better RF range than older digital technologies
- Forward Error Correction and Cyclic Redundancy Check coders

Better Audio Quality

- Listen for yourself. DMR does sound better than older digital technologies.



Longer Battery Life



Older Digital Modes
(FDMA)



DMR
(TDMA)

“For each hour of usage the TDMA radios show between 19% and 34% less battery capacity is required than for the FDMA models.”

“40 percent improvement in talk time in comparison with analogue radios “

Data and Voice at the Same Time



Slot 1 Voice



Slot 2 GPS Location


(or second channel voice when not sending GPS data)



Give your location WHILE talking!

IP Site Connect

1 or 2 slots (channels)



Dynamic Mixed Mode: First in – First Out



*Repeater dynamically detects the type of input
IP site connect currently not supported in DMM*

This is a stand-alone repeater option only.

Free Text Messaging



Send to one person, or a group of people.

- Weather Alerts
- Club Meetings
- Announcements

Monochrome Radios

- XPR6550 and cost reduced XPR3500 portables
- XPR4550 Mobile
- Make sure the radio is UHF1 (403-470 MHz) not 450-512 MHz (commercial band).



New Color Radios Now Available

- XPR7550 Portable
- XPR5550 Mobile
- SL7550 (slim line, looks like cell phone)



DMR Growth

| DATE (MM_YY) | # Radio IDs | # Repeaters | DMR-MARC | # Countries |
|--------------|-------------|-------------|----------|-------------|
| Jan-09 | 50 | 6 | | 2 |
| May-10 | 200 | 21 | | 3 |
| Feb-11 | 400 | 21 | | 3 |
| Sep-11 | 800 | 44 | | 6 |
| Dec-11 | 900 | 55 | | 8 |
| May-12 | 1591 | 152 | 83 | 8 |
| Jun-12 | 1796 | 164 | 85 | 9 |
| Jul-12 | 1874 | 169 | 86 | 9 |
| Jul-12 | 1911 | 175 | 86 | 9 |
| Aug-12 | 1941 | 178 | 86 | 9 |
| Sep-12 | 2091 | 188 | 90 | 10 |
| Sep-12 | 2140 | 191 | 91 | 10 |
| Dec-12 | 2376 | 211 | 100 | 10 |
| Jan-13 | 2510 | 230 | 100 | 10 |
| Feb-13 | 2653 | 245 | 135 | 10 |
| Mar-13 | 2864 | 265 | 140 | 12 |



- Motorola Amateur Radio Clubs and other private XPR8300/8400 and MTR3000 repeater owners
- 160 site network in USA, Germany, Australia, South Africa, New Zealand, Spain, Switzerland, Austria, Canada, Finland, Sweden, Italy, Mexico, and the UK.
- 100% Pure Digital. Voice and text messaging supported.
- Weekly nets to discuss technical issues
- More than 2700 registered users
- To register or learn more <http://dmr-marc.net>
- There you will also find links to our bridge partners, our Yahoo group and other programming aids.

Talk Groups Increase Capacity!

- Time Slot 1, Talk Group 3 – Native English speakers (USA, Canada, Australia, New Zealand, South Africa, and U.K.)
- Time Slot 1, Talk Group 1 – Primary English language countries to secondary English speaking Europeans
- Time Slot 2, talk group 2 – Local Repeater QSOs.
- Time Slot 2, first 4 digits of state ID (KS = 3120) for statewide linked TS2 systems. Also, country talk groups are 3 digits (Canada = 302)
- Be courteous and use the local time slot for local repeater QSOs and don't monopolize the linked network time slot 1 if you don't have to.

Talk Group Mappings



TG1, TS1 (World)

- Saturday Nets
- Calls to second language English speakers
- Don't use for UK-> USA or Australia-> Canada, etc.

TG3, TS1 (NAm/English)

- Calls to native English speakers
- Share with other users!
- Use local/regional TG/TS when possible



Other Talk Groups

| Network | Region | Talk Group ID | Assignment | Notes |
|-------------|---------------------------------------|---------------|----------------------------|--|
| DMR-MARC | Europe | 1 | Intercontinental | TS1 only |
| DMR-MARC | Europe | 2 | Europe Continental | TS1 |
| DMR-MARC | Europe | 9 | Europe Local Repeater | TS2 |
| DMR-MARC | Europe | 214 | Spain | TS1 or TS2 |
| DMR-MARC | Europe | 222 | Italy | TS2 |
| DMR-MARC | Europe | 228 | Switzerland | TS1 or TS2 |
| DMR-MARC | Europe | 232 | Austria | TS1 or TS2 |
| DMR-MARC | Europe | 235 | United Kingdom | TS2 |
| DMR-MARC | Europe | 240 | Sweden | TS1 or TS2 |
| DMR-MARC | Europe | 244 | Finland | TS1 or TS2 |
| DMR-MARC | Europe | 262 | Germany | TS1 or TS2 |
| DMR-MARC | N. America, UK, S. Pacific, S. Africa | 1 | Intercontinental | TS1 only, use only for Sat. nets and calls to Europe |
| DMR-MARC | N. America, UK, S. Pacific, S. Africa | 3 | N. America | TS1 only, All English speaking countries |
| DMR-MARC | S. Pacific | 5 | Australia/New Zealand Only | TS2 |
| DMR-MARC | N. America | 302 | Canada | |
| DMR-MARC | N. America | 334 | Mexico | TS2 |
| DCI | N. America | 3100 | DCI Bridge | |
| GA-DMR | N. America | 3113 | GA Statewide | TS 2 |
| SF-TRBO | N. America | 3115 | HI Statewide | TS 2 |
| MIT | N. America | 3125 | New England Network | TS 2 |
| DCI | N. America | 3126 | MI Statewide | TS 2 |
| KØUSY Group | N. America | 3130 | KS Statewide | TS 2 |
| NorCal | N. America | 3148 | TX Statewide | TS 2 |
| DCI | N. America | 3153 | WA Statewide | |
| DCI | N. America | 3160 | DCI 1 | |
| DCI | N. America | 3161 | DMR-MARC World | TS2 |
| DCI | N. America | 3162 | DCI 2 | |
| DCI | N. America | 3163 | DMR-MARC N. Am. | TS2 |
| DCI | N. America | 3166 | Test1 | |
| DCI | N. America | 3167 | Net1 | |
| DCI | N. America | 3168 | I-5 | CA, OR, WA |
| DMR-MARC | N. America | 3170 | Midwest USA | TS2 |
| N. Colorado | N. America | 3171 | N. Colorado | TS2 |
| DMR-MARC | S. Pacific | 5054 | Queensland | TS 2 |

ID Scheme

- DMR supports 16777215 IDs. We ask max 2 IDs per person. You can reuse same ID on multiple radios that you use-> Recommended!
- 8-digits: Admin tools and resources
- 7-digits: Subscribers (mobiles and portables)
- 6-digits: Repeaters
- 4-digits: Regional Talk Groups
- 3 digits: Country Talk groups

Examples: Subscriber IDs are 7 digits: XXXYZZZ
where XXX= Country
Y= State/Province
ZZZ= Sequentially assigned subscriber number

Repeater IDs are 6 digits: XXXYWW
where XXX= Country
Y= State/Province
WW= Sequentially assigned repeater number

Common Courtesy

- ALL RADIOS MUST HAVE A VALID 7-DIGIT DMR ID from our website <http://dmr-marc.net>, Under “Contact Us” Radios without an official ID should not be on the system. Period. Do not make up your own ID.
- Do not key up on TS1 and blow into mic to test your radio. You key up 100+ repeaters and that is annoying to all of us who listen.
- Do radio tests on TS2 with a voice ID.
- You must identify your callsign just like you did in the past on an analog repeater per FCC rules.

Status of C-bridge

- Links master repeaters (groups of 15-20), and bridges
- Mfr: Rayfield Communications Springfield, MO
- We have 6 masters (Chicago, S. NH, S. FL, Montreal, Toronto, and Brisbane), and 14 bridges connected to the DMR-MARC C-bridge and the DMR-MARC-IL C-bridges
- We have connections to multiple bridge partners including DCI (WA), NC-PRN, NorCal, AZ TRBO, WØPM (MO), KØUSY (KS), Georgia DMR, SF TRBO, N2JTI (NJ), N2NSA (NY), N. CO, Denver, Vancouver)

Current Development Projects


- TRBO to APRS-IS. Currently working on FCC ID compliance.
- Automated severe weather warnings to local time slot on radio
- Join our MOTOTRBO Yahoo group to help!



Ham Friendly Dealers

- Rayfield Communications, contact John Rayfield, Jr 800.743.9711. Mention you are part of MARC and inquire about ham pricing.
- Sandy's Communications in Mission Hills, CA
- E-Bay or Local Dealer
- TRBO DMR radios are DMR –and- Analog monoband
- Mobile: XPR4550 UHF band 1 (403-470 MHz) 25-45W, Portable: XPR6550 UHF band 1

Customer Programming SW



C-Bridge Last Heard/Net Status

Firefox

Rayfield Comm

Go to a Website

Most Visited Getting Started DRUDGE REPORT Gmail Yahoo! Mail Chicago Sports Chicagoland Skywarn AA9VI QRZ Chicago AVS Forum Bookmarks

DMR-MARC
National Amateur Radio Club Worldwide Network

Control Center DMR-MARC

6913.2013.4.22
23:18:31 May 02, 2013
aa9vi Single connection Log Out

Home Config Connections Calls Diagnostics Netwatch Help

Gateway (1)
DMR-MARC

Total calls
282 Network
331 Local

Network watch Filter Peer CC-CC Current Voice Call Data Call Destination

Active Peers

| W8FSM - Fenton MI | 13128203 | 13129101 | 0 | 1282208 | 13128208 | | | | | | |
|-----------------------|----------|----------|----------|---------|----------|--------|---------|----------|----------|----------|--|
| W4MOT - Plantation FL | 311203 | 13129102 | 312400 | 312401 | 313900 | 315100 | 315101 | 1262204 | 13124502 | 13126207 | |
| K9MOT - Schaumburg IL | 311702 | 13129103 | 310804 | 312606 | 313100 | 313202 | 334301 | 1262202 | 13126208 | | |
| NE1B - Hudson NH | 313300 | 13129104 | 312602 | 313301 | 313302 | 313605 | 1262218 | 13124503 | 13126219 | | |
| K6EH - Los Angeles CA | 310699 | 13129105 | 13106203 | | | | | | | | |

CC-CC

DMR-IL Browse-TRBO DMR-MARC-IL PRN-Network AZ-TRBONET CO-RMHR NJ-TRBO GeorgiaDMR DMR-MARC-IL DMR-MARC-IL


Current Talker

| start time | duration | ch | name | source peer id | source radio id | source peer alias | source radio alias | Group ID | RSSI (dBm) | site name |
|------------------|----------|----|------------------------|----------------|-----------------|--|--------------------|----------|------------|-----------|
| 23:15:45.3 May/2 | 3.8 | 6 | Chicagoland Local | g 313202 | 3132016 | Elko - Nevada - USA -- KB78JZ | 3132016 | 2353003 | -67.9 | DMR-MARC |
| 22:52:02.4 May/2 | 8.5 | 8 | New England Local | g 312502 | 3125002 | Southboro - Massachusetts - USA -- W1EMC | 3125002 | 2353003 | -102.3 | DMR-MARC |
| 22:47:16.7 May/2 | 1.6 | 6 | Chicagoland Local | g 334301 | 0 | Cancun - Quintana Roo - Mexico -- XE3RCC | 31110 | | -103.6 | DMR-MARC |
| 22:47:09.3 May/2 | 3.1 | 6 | Chicagoland Local | g 334301 | 1204 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1204 | 111 | -100.8 | DMR-MARC |
| 22:43:02.7 May/2 | 0.9 | 6 | Chicagoland Local | g 311702 | 3117271 | Schaumburg - Illinois - USA -- K9MOT | 3117271 | 2353003 | -99.3 | DMR-MARC |
| 22:39:34.7 May/2 | 0.5 | 6 | Chicagoland Local | g 311702 | 3117271 | Schaumburg - Illinois - USA -- K9MOT | 3117271 | 2353003 | -96.6 | DMR-MARC |
| 22:37:09.0 May/2 | 0.9 | 5 | NA-WW | g 310804 | 3108097 | Denver - Colorado - USA -- W0TX | 3108097 | 2353003 | -127.4 | DMR-MARC |
| 22:37:05.3 May/2 | 0.7 | 5 | NA-WW | g 310804 | 3108097 | Denver - Colorado - USA -- W0TX | 3108097 | 2353003 | | DMR-MARC |
| 22:33:35.0 May/2 | 4.9 | 6 | Chicagoland Local | g 334301 | 3343001 | Cancun - Quintana Roo - Mexico -- XE3RCC | 3343001 | 111 | -80.0 | DMR-MARC |
| 22:33:31.7 May/2 | 0.5 | 6 | Chicagoland Local | g 334301 | 1202 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1202 | 222 | -109.1 | DMR-MARC |
| 22:33:16.5 May/2 | 13.8 | 6 | Chicagoland Local | g 334301 | 1204 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1204 | 111 | -107.8 | DMR-MARC |
| 22:33:16.5 May/2 | 11.3 | 6 | Chicagoland Local | g 334301 | 1204 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1204 | 111 | -81.2 | DMR-MARC |
| 22:33:16.5 May/2 | 5.5 | 6 | Chicagoland Local | g 334301 | 1204 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1204 | 111 | -98.2 | DMR-MARC |
| 22:33:11.4 May/2 | 3.8 | 6 | Chicagoland Local | g 334301 | 3343001 | Cancun - Quintana Roo - Mexico -- XE3RCC | 3343001 | 111 | -84.4 | DMR-MARC |
| 22:32:56.1 May/2 | 13.9 | 6 | Chicagoland Local | g 334301 | 1204 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1204 | 111 | -105.3 | DMR-MARC |
| 22:32:50.3 May/2 | 3.8 | 6 | Chicagoland Local | g 334301 | 3343001 | Cancun - Quintana Roo - Mexico -- XE3RCC | 3343001 | 111 | -79.3 | DMR-MARC |
| 22:32:51.1 May/2 | 0.9 | 6 | North America CC - DCI | p 315306 | 3153011 | Seattle - Washington - USA -- NF6C | 3153011 | | -125.6 | T6-DCI |

Voice Log

| start time | duration | ch | name | source peer id | source radio id | source peer alias | source radio alias | Group ID | RSSI (dBm) | site name |
|------------------|----------|----|------------------------|----------------|-----------------|--|--------------------|----------|------------|-----------|
| 23:15:45.3 May/2 | 3.8 | 6 | Chicagoland Local | g 313202 | 3132016 | Elko - Nevada - USA -- KB78JZ | 3132016 | 2353003 | -67.9 | DMR-MARC |
| 22:52:02.4 May/2 | 8.5 | 8 | New England Local | g 312502 | 3125002 | Southboro - Massachusetts - USA -- W1EMC | 3125002 | 2353003 | -102.3 | DMR-MARC |
| 22:47:16.7 May/2 | 1.6 | 6 | Chicagoland Local | g 334301 | 0 | Cancun - Quintana Roo - Mexico -- XE3RCC | 31110 | | -103.6 | DMR-MARC |
| 22:47:09.3 May/2 | 3.1 | 6 | Chicagoland Local | g 334301 | 1204 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1204 | 111 | -100.8 | DMR-MARC |
| 22:43:02.7 May/2 | 0.9 | 6 | Chicagoland Local | g 311702 | 3117271 | Schaumburg - Illinois - USA -- K9MOT | 3117271 | 2353003 | -99.3 | DMR-MARC |
| 22:39:34.7 May/2 | 0.5 | 6 | Chicagoland Local | g 311702 | 3117271 | Schaumburg - Illinois - USA -- K9MOT | 3117271 | 2353003 | -96.6 | DMR-MARC |
| 22:37:09.0 May/2 | 0.9 | 5 | NA-WW | g 310804 | 3108097 | Denver - Colorado - USA -- W0TX | 3108097 | 2353003 | -127.4 | DMR-MARC |
| 22:37:05.3 May/2 | 0.7 | 5 | NA-WW | g 310804 | 3108097 | Denver - Colorado - USA -- W0TX | 3108097 | 2353003 | | DMR-MARC |
| 22:33:35.0 May/2 | 4.9 | 6 | Chicagoland Local | g 334301 | 3343001 | Cancun - Quintana Roo - Mexico -- XE3RCC | 3343001 | 111 | -80.0 | DMR-MARC |
| 22:33:31.7 May/2 | 0.5 | 6 | Chicagoland Local | g 334301 | 1202 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1202 | 222 | -109.1 | DMR-MARC |
| 22:33:16.5 May/2 | 13.8 | 6 | Chicagoland Local | g 334301 | 1204 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1204 | 111 | -107.8 | DMR-MARC |
| 22:33:16.5 May/2 | 11.3 | 6 | Chicagoland Local | g 334301 | 1204 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1204 | 111 | -81.2 | DMR-MARC |
| 22:33:16.5 May/2 | 5.5 | 6 | Chicagoland Local | g 334301 | 1204 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1204 | 111 | -98.2 | DMR-MARC |
| 22:33:11.4 May/2 | 3.8 | 6 | Chicagoland Local | g 334301 | 3343001 | Cancun - Quintana Roo - Mexico -- XE3RCC | 3343001 | 111 | -84.4 | DMR-MARC |
| 22:32:56.1 May/2 | 13.9 | 6 | Chicagoland Local | g 334301 | 1204 | Cancun - Quintana Roo - Mexico -- XE3RCC | 1204 | 111 | -105.3 | DMR-MARC |
| 22:32:50.3 May/2 | 3.8 | 6 | Chicagoland Local | g 334301 | 3343001 | Cancun - Quintana Roo - Mexico -- XE3RCC | 3343001 | 111 | -79.3 | DMR-MARC |
| 22:32:51.1 May/2 | 0.9 | 6 | North America CC - DCI | p 315306 | 3153011 | Seattle - Washington - USA -- NF6C | 3153011 | | -125.6 | T6-DCI |

Copyright (c) 2004-2012 RavenNet Systems(tm)



RDACrepeater diagnostics and control

Systems

Options

RDAC Log

Connect

IP Site Mode

Help

K9MOT-Sch

| | Alarms | Radio ID | Radio Name | Service | Firmware Version | State | Channel Name | TX Power | RX Alarm | TX Alarm | Temp Alarm | AC Power Alarm | Fan Alarm | VSWR Alarm | TX Power Alarm |
|---|--------|----------|------------------|---------|------------------|---------|----------------|----------|----------|----------|------------|----------------|-----------|------------|----------------|
| ▶ | ● | 311702 | K9MOT-Schaumburg | Master | R01.07.02 | Enabled | 444.79375 T12 | High | ● | ● | ● | ● | ● | ● | ● |
| | ● | 262410 | DF0MHR Muelheim | Peer | R01.07.00 | Enabled | IP-DIG TS1 TS2 | Low | ● | ● | ● | ● | ● | ● | ● |
| | ● | 262100 | DM0MOT Berlin | Peer | R01.07.00 | Enabled | IP-DIG TS1 TS2 | High | ● | ● | ● | ● | ● | ● | ● |
| | ● | 262430 | DB0AVR Alsdorf | Peer | R01.07.00 | Enabled | IP-DIG TS1 TS2 | High | ● | ● | ● | ● | ● | ● | ● |
| | ● | 262450 | DB0ZO Doerenberg | Peer | R01.06.20 | Enabled | IP-DIG TS1 TS2 | High | ● | ● | ● | ● | ● | ● | ● |
| | ● | 310400 | KE7JFH Mesa AZ | Peer | R01.07.02 | Enabled | WIDE1 | High | ● | ● | ● | ● | ● | ● | ● |
| | ● | 262601 | DF0MOT Frankfurt | Peer | R01.07.00 | Enabled | IP-DIG TS1 TS2 | High | ● | ● | ● | ● | ● | ● | ● |
| | ● | 310600 | N6DVA Los Angele | Peer | R01.07.00 | Enabled | IP-DIG TS1 | High | ● | ● | ● | ● | ● | ● | ● |
| | ● | 311202 | N4AMC LalelandFI | Peer | R01.07.00 | Enabled | Dig-Not Linked | High | ● | ● | ● | ● | ● | ● | ● |
| | ▲ | 311203 | W4MOT-PlantatnFL | Peer | R01.07.00 | Enabled | 443 TS1 | High | ● | ● | ● | ● | ● | ● | ▲ |
| | ● | 312900 | 312900-KC | Peer | R01.07.02 | Enabled | World 1 Net | Low | ● | ● | ● | ● | ● | ● | ● |
| | ● | 313100 | K0BOY Omaha NE | Peer | R01.07.00 | Enabled | IP-DIG TS1 | Low | ● | ● | ● | ● | ● | ● | ● |
| | ● | 315100 | W4YP - Haymarket | Peer | R01.07.02 | Enabled | Digital TS1 | High | ● | ● | ● | ● | ● | ● | ● |
| | ● | 3124100 | N3LHD-Wash DC | Peer | R01.07.00 | Enabled | IP-DIG TS1 | High | ● | ● | ● | ● | ● | ● | ● |
| | ● | 505600 | vk6ztn-1 | Peer | R01.07.02 | Enabled | Channel1 | High | ● | ● | ● | ● | ● | ● | ● |

Diagnostics

RSSI Slot 1

-88.95

RSSI Slot 2

-123.11

Read RSSI

Repeater Log

| Name | Type | State | Time (sec) |
|------|------|-------|------------|
| | | | |

Save Log

Read Log

Clear Log

Control

Current Channel 444.79375 T12

TX Power High

State Enabled

Knockdown Knockdown

⚠ Clicking Write or Reset will reset the repeater. It may not be available for 8-10 secs.

Reset

Write

Reload

Acknowledgements

- NE1B and KBØZZT for the DMR Growth Stats
- Rayfield Communications- C-Bridge
- ElComPlus – SmartPTT
- WØWJB – Network Hosting, 2012 Hamvention Booth
- K6EH- Webpage Hosting
- DMR-MARC members for 2013 Hamvention Booth



Backup Slides

GW3TRBO – Who's on Where?

Activity (Admin)

FilterPauseViewHelp

Connected to Module: Ye

Packet Types

☒ [Call Activity] Channel Assignment: Group

☒ [Call Activity] Channel Assignment: Group Radio Data

☒ [Call Activity] Channel Assignment: Private

☒ [Call Activity] Channel Assignment: Private Radio Data

☐ [LE] Deregistration Request

☐ [LE] Deregistration Response

☐ [LE] Master Keep Alive Request

Press F1 for Help

Select All

Unselect All

| Site ID | Site ID Alias | Type | Group | ID Alias | ID | Target ID Ali | Timestamp | Elapsed T |
|---------|-----------------------|-------|-------|-------------------|---------|---------------|------------------------|-----------|
| 310699 | DMR-MARCC-BRIDGE | Group | 1 | K6EH - PAUL P1 | 3106001 | | 7/14/2011 01:15:31.781 | 00:00:00. |
| 2000 | | | | Peer 2000 | 2000 | Peer 311210 | 7/14/2011 00:42:37.484 | |
| 262410 | DFOMHR - Muelheim EU | | | | | Peer 262410 | 7/14/2011 00:30:16.671 | |
| 262410 | DFOMHR - Muelheim EU | | | | | Peer 262410 | 7/14/2011 00:30:06.406 | |
| 2000 | | | | Peer 2000 | 2000 | Peer 262410 | 7/14/2011 00:29:42.296 | |
| 7 | | | | | | Peer 7 | 7/14/2011 00:25:15.843 | |
| 7 | | | | | | Peer 7 | 7/14/2011 00:22:41.562 | |
| 310699 | DMR-MARCC-BRIDGE | Group | 1 | K6EH - PAUL P1 | 3106001 | | 7/13/2011 23:51:56.640 | 00:00:00. |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:51:20.343 | 00:00:00. |
| 311702 | K9MOT - Schaumburg IL | Group | 1 | AA9VI - MIKE M | 3117121 | | 7/13/2011 23:50:55.625 | 00:00:15. |
| 2001 | | | | | | Peer 2001 | 7/13/2011 23:50:55.250 | |
| 311702 | K9MOT - Schaumburg IL | Group | 1 | AA9VI - MIKE M | 3117121 | | 7/13/2011 23:50:40.500 | 00:00:00. |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:50:35.250 | 00:00:28. |
| 2001 | | | | | | Peer 2001 | 7/13/2011 23:50:35.156 | |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:50:07.515 | 00:00:00. |
| 311702 | K9MOT - Schaumburg IL | Group | 1 | AA9VI - MIKE M | 3117121 | | 7/13/2011 23:49:25.515 | 00:00:00. |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:49:00.937 | 00:00:00. |
| 311702 | K9MOT - Schaumburg IL | Group | 1 | AA9VI - MIKE M | 3117121 | | 7/13/2011 23:48:02.468 | 00:00:00. |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:47:58.203 | 00:00:00. |
| 311702 | K9MOT - Schaumburg IL | Group | 1 | AA9VI - MIKE M | 3117121 | | 7/13/2011 23:47:53.000 | 00:00:00. |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:47:24.953 | 00:00:00. |
| 310699 | DMR-MARCC-BRIDGE | Group | 1 | K6EH - PAUL P1 | 3106001 | | 7/13/2011 23:47:09.453 | 00:00:00. |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:46:42.890 | 00:00:00. |
| 310699 | DMR-MARCC-BRIDGE | Group | 1 | K6EH - PAUL P1 | 3106001 | | 7/13/2011 23:45:27.812 | 00:00:00. |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:45:06.359 | 00:00:00. |
| 310699 | DMR-MARCC-BRIDGE | Group | 1 | K6EH - PAUL P1 | 3106001 | | 7/13/2011 23:44:27.390 | 00:00:00. |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:44:02.843 | 00:00:00. |
| 310699 | DMR-MARCC-BRIDGE | Group | 1 | K6EH - PAUL P1 | 3106001 | | 7/13/2011 23:43:20.781 | 00:00:00. |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:43:01.937 | 00:00:00. |
| 310699 | DMR-MARCC-BRIDGE | Group | 1 | K6EH - PAUL P1 | 3106001 | | 7/13/2011 23:42:44.546 | 00:00:00. |
| 311203 | N4AMC - Lakeland FL | Group | 1 | W4RCC - Richard P | 3112010 | | 7/13/2011 23:42:36.406 | 00:00:00. |